

850 Series

Generation 6 MX Engineering Management Tool



The 850EMT Engineering Management Tool is a powerful and flexible tool used in the installation, commissioning, diagnostics and servicing of Tyco MX detection systems.

Features

- // Simplifies installation & commissioning
- // Bidirectional IR link allows remote detector programming, interrogation and testing
- // Programs all MX Detectors & Ancillaries
- // 320x240 QVGA Backlit TFT Touch Screen

When used with VIGILANT MX1 systems, the 850EMT can remotely interrogate, address and test the 850 Series detectors. Alternatively, any MX detector can plug on directly; MX modules are connected using an ancillary lead (supplied).

Bidirectional IR Link

The ability of the 850EMT to communicate with the 850 series detectors on a VIGILANT MX1 using a bidirectional infrared wireless link is unique. This feature allows you to better manage the commissioning and servicing of 850 Series detectors from ground level without the requirements of high ladders or cherry pickers. Programming, testing and verification of a detector can be carried out by a single visit to the device - from the ground. This is a major benefit: saving you time, costs and the health and safety of your commissioning technicians.

The 850EMT Kit consists of:

- 850EMT Service Tool
- 6x AA NiMH rechargeable batteries
- 240VAC mains adaptor
- 12Vdc car adaptor
- Ancillary programming lead
- Spare pins for the programming lead
- Carry case and shoulder strap.



Specifications

Dimensions	48 x 200 x 112mm
Weight	500g incl. batteries
Battery	6x AA NiMH rechargeable
Battery Life	up to 15 hrs operation/charge
Mains	240VAC to 12Vdc Adaptor
IR Range (selectable)	up to 5m / 5m to 15m
Ambient Temperature	0°C to +50°C
Relative Humidity	10% to 95% (non cond.)

Part Numbers

850EMTK	850EMT Service Tool Kit
516.850.904	Stylus
516.800.922	Ancillary Lead
516.800.923	Carry Case & Accessories
516.800.924	Anc. Lead Spare Pins (Pk 10)



850EMTK 850EMT Service Tool Kit



Left Side View
 1 - DC IN 12V External Connector
 2 - Power On/Off Switch



Right Side View
 1 - AUX Cable Port
 2 - COM Port
 3 - Belt Strap Holder
 4 - Stylus



Top View
 1 – Detector on Tool Base
 Twist detector clockwise to engage and lock in position
 2 – Ancillary Lead
 Used for programming MX devices
 3 – Escape Button
 4 – OK Button
 5 – Up Arrow Button
 6 – Down Arrow Button
 7 - LCD Touch Screen

Access Information

To access all the available options, you need to log on using a standard PIN.

Once successfully logged in, there are 5 options including: DEVICE STATUS, SESSION PROGRAM, COMMUNICATION MODE, TEST FUNCTIONS, 850EMT SETTINGS.

Australia

Tyco Fire Protection Products
 Level 3, 95 Coventry Street
 Southbank VIC 3006
 Tel : 1300 725 688
 Tel : +61 3 9313 9700
 Email : tfppcustservice.au@tycofp.com

New Zealand

Tyco Fire Protection Products
 17 Mary Muller Drive
 Hillsborough PO Box 19-545
 Woolston Christchurch 8241
 Tel : +64 9 635 0760
 Email : tsp.sales.nz@tycoint.com

Copyright © 2015 Tyco Australia Pty Limited. All rights reserved. Tyco reserves the right to make changes to any aspect of this publication at any time without notice. VIGILANT is a trademark of Tyco New Zealand Limited or its affiliates; TYCO is a trademark of Tyco International Services GmbH. 850EMTdatTFPP1505